

## SD - 112S · SD - 112F2

The SD - 112, 112F2 are position sensors for automatic focusing of camera.

**FEATURES**


- Visible ray cut off flat package
- Laser beam focusing/positioning is best performed
- With alignment hole

**APPLICATIONS**

- Automatic focusing of camera

**DIMENSIONS**

(Unit : mm)

**MAXIMUM RATINGS**

(Ta=25 °C)

Item	Symbol	Rating	Unit
Reverse voltage	$V_R$	30	V
Power dissipation	$P_D$	30	mW
Operating temp.	Topr.	- 25 ~ +85	
Storage temp.	Tstg.	- 30 ~ +100	
Soldering temp.	Tsol.	260	

**ELECTRO-OPTICAL CHARACTERISTICS**

(Ta=25 °C)

Item	Symbol	Conditions	Min.	Typ.	Max.	Unit.
Reverse voltage	$V_R$	$I_R = 10 \mu A$	30			V
Dark current	$I_d$	$V_R = 1V$			5	nA
Light current	$I_L$ <sup>*1</sup>	$V_R = 1V, E = 1000lx^5$	9	11		$\mu A$
Spectral sensitivity				700 ~ 1100		nm
Peak wavelength	$\lambda_p$			920		nm
Switching speeds	$t_r, t_f$	$V_R = 1V, R_L = 1K$		2		$\mu sec.$
Capacitance	$C_t$	$V_R = 1V, f = 1MHz$		10		pF
Resistance	$R_s$ <sup>*2</sup>	$V_R = 1V, V_a = 0.5V$		150	200	K
Signal slope		$V_R = 1V$	100	0.100		-
Light current difference	$I_L / I_L$ <sup>*4</sup>				$\pm 2$	%

\*1.  $I_L = I_1 + I_2$  ( $I_1$  = Light current of A1,  $I_2$  = Light current of A2)

\*2.  $V_a$  = Voltage of Anode A1, A2

\*3.  $I_L = I_1 - I_2$  ( $I_1$  = Light current of A1,  $I_2$  = Light current of A2)


\*4.  $I_L = I_1 - I_2$

\*5. Color temp. = 2856K standard Tungsten lamp


## Position Sensitive Diode

SD - 112S· SD - 112F2


**Power dissipation Vs. Ambient temperature**




**Light current Vs. Illuminance**




**Relative sensitivity Vs. Wavelength**




**Relative light current Vs. Ambient temperature**




**Relative resistance between electrodes Vs. Ambient temperature**




**Dark current Vs. Ambient temperature**



**Dark current Vs. Reverse voltage**



**Capacitance between terminals Vs. Reverse voltage**



**Relative light current Vs. Position**

