

# 74AHC2G126; 74AHCT2G126

Dual buffer/line driver; 3-state

Rev. 01 — 4 March 2004

Product data sheet

## 1. General description

The 74AHC2G126; AHCT2G126 is a high-speed Si-gate CMOS device.

The 74AHC2G126; AHCT2G126 provides a dual non-inverting buffer/line driver with 3-state output. The 3-state output is controlled by the output enable input (OE). A LOW at pin nOE causes the output to assume a high-impedance OFF-state.

## 2. Features

- Symmetrical output impedance
- High noise immunity
- ESD protection:
  - ◆ HBM EIA/JESD22-A114-A exceeds 2000 V
  - ◆ MM EIA/JESD22-A115-A exceeds 200 V
  - ◆ CDM EIA/JESD22-C101 exceeds 1000 V.
- Low power dissipation
- Balanced propagation delays
- SOT505-2 and SOT765-1 package
- Specified from -40 °C to +85 °C and from -40 °C to +125 °C.

## 3. Quick reference data

**Table 1: Quick reference data**

GND = 0 V;  $T_{amb}$  = 25 °C;  $t_r = t_f \leq 3.0$  ns.

| Symbol                 | Parameter                        | Conditions                    | Min    | Typ | Max | Unit |
|------------------------|----------------------------------|-------------------------------|--------|-----|-----|------|
| <b>Type 74AHC2G126</b> |                                  |                               |        |     |     |      |
| $t_{PHL}, t_{PLH}$     | propagation delay<br>nA to nY    | $C_L = 15$ pF; $V_{CC} = 5$ V | -      | 3.4 | 5.5 | ns   |
| $C_I$                  | input capacitance                |                               | -      | 1.5 | 10  | pF   |
| $C_{PD}$               | power dissipation<br>capacitance | $C_L = 50$ pF; $f_i = 1$ MHz  | [1][2] | -   | 10  | -    |

**PHILIPS**

**Table 1:** Quick reference data ...continued  
 $GND = 0 \text{ V}$ ;  $T_{amb} = 25^\circ\text{C}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ .

| Symbol                  | Parameter                        | Conditions                                  | Min    | Typ | Max | Unit |    |
|-------------------------|----------------------------------|---|--------|-----|-----|------|----|
| <b>Type 74AHCT2G126</b> |                                  |   |        |     |     |      |    |
| $t_{PHL}, t_{PLH}$      | propagation delay<br>nA to nY    | $C_L = 15 \text{ pF}; V_{CC} = 5 \text{ V}$ | -      | 3.4 | 5.5 | ns   |    |
| $C_I$                   | input capacitance                |   | -      | 1.5 | 10  | pF   |    |
| $C_{PD}$                | power dissipation<br>capacitance | $C_L = 50 \text{ pF}; f_i = 1 \text{ MHz}$  | [1][2] | -   | 10  | -    | pF |

[1]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ).

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \sum(C_L \times V_{CC}^2 \times f_o) \text{ where:}$$

$f_i$  = input frequency in MHz;

$f_o$  = output frequency in MHz;

$C_L$  = output load capacitance in pF;

$V_{CC}$  = supply voltage in Volts;

N = total load switching outputs;

$\sum(C_L \times V_{CC}^2 \times f_o)$  = sum of the outputs.

[2] The condition is  $V_I = GND$  to  $V_{CC}$ .

## 4. Ordering information

**Table 2:** Ordering information

| Type number   | Package           |        |  |          | Version |
|---------------|-------------------|--------|--|----------|---------|
|               | Temperature range | Name   | Description  | Version  |         |
| 74AHC2G126DP  | −40 °C to +125 °C | TSSOP8 | plastic thin shrink small outline package;<br>8 leads; body width 3 mm; lead length 0.5 mm | SOT505-2 |         |
| 74AHCT2G126DP | −40 °C to +125 °C | TSSOP8 | plastic thin shrink small outline package;<br>8 leads; body width 3 mm; lead length 0.5 mm | SOT505-2 |         |
| 74AHC2G126DC  | −40 °C to +125 °C | VSSOP8 | plastic very thin shrink small outline package;<br>8 leads; body width 2.3 mm              | SOT765-1 |         |
| 74AHCT2G126DC | −40 °C to +125 °C | VSSOP8 | plastic very thin shrink small outline package;<br>8 leads; body width 2.3 mm              | SOT765-1 |         |

## 5. Marking

**Table 3:** Marking

| Type number   | Marking code |
|---------------|--------------|
| 74AHC2G126DP  | A26          |
| 74AHCT2G126DP | C26          |
| 74AHC2G126DC  | A26          |
| 74AHCT2G126DC | C26          |

## 6. Functional diagram




Fig 1. Logic symbol.




Fig 2. IEC logic symbol.




Fig 3. Logic diagram.

## 7. Pinning information

### 7.1 Pinning




Fig 4. Pin configuration.

### 7.2 Pin description

Table 4: Pin description

| Pin | Symbol          | Description                       |
|-----|-----------------|-----------------------------------|
| 1   | 1OE             | output enable input (active HIGH) |
| 2   | 1A              | data input                        |
| 3   | 2Y              | data output                       |
| 4   | GND             | ground (0 V)                      |
| 5   | 2A              | data input                        |
| 6   | 1Y              | data output                       |
| 7   | 2OE             | output enable input (active HIGH) |
| 8   | V <sub>CC</sub> | supply voltage                    |

## 8. Functional description

### 8.1 Function table

Table 5: Function table [1]

| Input |    | Output |
|-------|----|--------|
| nOE   | nA | nY     |
| H     | L  | L      |
| H     | H  | H      |
| L     | X  | Z      |

[1] H = HIGH voltage level;  
 L = LOW voltage level;  
 X = don't care;  
 Z = high-impedance OFF-state.

## 9. Limiting values

Table 6: Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). Voltages are referenced to GND (ground = 0 V).

| Symbol                             | Parameter                      | Conditions  | Min  | Max  | Unit |    |
|------------------------------------|--------------------------------|---|------|------|------|----|
| V <sub>CC</sub>                    | supply voltage                 |   | -0.5 | +7.0 | V    |    |
| V <sub>I</sub>                     | input voltage                  |   | -0.5 | +7.0 | V    |    |
| I <sub>IK</sub>                    | input diode current            | V <sub>I</sub> < -0.5 V   | -    | -20  | mA   |    |
| I <sub>OK</sub>                    | output diode current           | V <sub>O</sub> < -0.5 V or V <sub>O</sub> > V <sub>CC</sub> + 0.5 V | [1]  | -    | ±20  | mA |
| I <sub>O</sub>                     | output source or sink current  | V <sub>O</sub> > -0.5 V or V <sub>O</sub> < V <sub>CC</sub> + 0.5 V | -    | ±25  | mA   |    |
| I <sub>CC</sub> , I <sub>GND</sub> | V <sub>CC</sub> or GND current |   | -    | ±75  | mA   |    |
| T <sub>stg</sub>                   | storage temperature            |   | -65  | +150 | °C   |    |
| P <sub>tot</sub>                   | power dissipation              | T <sub>amb</sub> = -40 °C to +125 °C                                | -    | 250  | mW   |    |

[1] The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

## 10. Recommended operating conditions

Table 7: Recommended operating conditions

| Symbol                          | Parameter                     | Conditions   | Min | Typ | Max             | Unit |
|---------------------------------|-------------------------------|--|-----|-----|-----------------|------|
| <b>Type 74AHC2G126</b>          |                               |  |     |     |                 |      |
| V <sub>CC</sub>                 | supply voltage                |  | 2.0 | 5.0 | 5.5             | V    |
| V <sub>I</sub>                  | input voltage                 |  | 0   | -   | 5.5             | V    |
| V <sub>O</sub>                  | output voltage                |  | 0   | -   | V <sub>CC</sub> | V    |
| T <sub>amb</sub>                | operating ambient temperature | see <a href="#">Section 11</a> and <a href="#">Section 12</a> per device | -40 | +25 | +125            | °C   |
| t <sub>r</sub> , t <sub>f</sub> | input rise and fall times     | V <sub>CC</sub> = 3.3 ± 0.3 V  | -   | -   | 100             | ns/V |
|                                 |                               | V <sub>CC</sub> = 5.0 ± 0.5 V  | -   | -   | 20              | ns/V |

**Table 7: Recommended operating conditions ...continued**

| Symbol                          | Parameter                     | Conditions   | Min | Typ | Max             | Unit |
|---------------------------------|-------------------------------|--|-----|-----|-----------------|------|
| <b>Type 74AHCT2G126</b>         |                               |  |     |     |                 |      |
| V <sub>CC</sub>                 | supply voltage                |  | 4.5 | 5.0 | 5.5             | V    |
| V <sub>I</sub>                  | input voltage                 |  | 0   | -   | 5.5             | V    |
| V <sub>O</sub>                  | output voltage                |  | 0   | -   | V <sub>CC</sub> | V    |
| T <sub>amb</sub>                | operating ambient temperature | see <a href="#">Section 11</a> and <a href="#">Section 12</a> per device | -40 | +25 | +125            | °C   |
| t <sub>r</sub> , t <sub>f</sub> | input rise and fall times     | V <sub>CC</sub> = 5.0 ± 0.5 V  | -   | -   | 20              | ns/V |

## 11. Static characteristics

**Table 8: Static characteristics type 74AHC2G126**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

| Symbol                         | Parameter  | Conditions   | Min  | Typ  | Max  | Unit |
|--------------------------------|--|--|------|------|------|------|
| <b>T<sub>amb</sub> = 25 °C</b> |  |  |      |      |      |      |
| V <sub>IH</sub>                | HIGH-level input voltage                         | V <sub>CC</sub> = 2.0 V  | 1.5  | -    | -    | V    |
|                                |  | V <sub>CC</sub> = 3.0 V  | 2.1  | -    | -    | V    |
|                                |  | V <sub>CC</sub> = 5.5 V  | 3.85 | -    | -    | V    |
| V <sub>IL</sub>                | LOW-level input voltage                          | V <sub>CC</sub> = 2.0 V  | -    | -    | 0.5  | V    |
|                                |  | V <sub>CC</sub> = 3.0 V  | -    | -    | 0.9  | V    |
|                                |  | V <sub>CC</sub> = 5.5 V  | -    | -    | 1.65 | V    |
| V <sub>OH</sub>                | HIGH-level output voltage                        | V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub>                                    |      |      |      |      |
|                                |  | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 2.0 V                                       | 1.9  | 2.0  | -    | V    |
|                                |  | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 3.0 V                                       | 2.9  | 3.0  | -    | V    |
|                                |  | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 4.5 V                                       | 4.4  | 4.5  | -    | V    |
|                                |  | I <sub>O</sub> = -4.0 mA; V <sub>CC</sub> = 3.0 V                                      | 2.58 | -    | -    | V    |
|                                |  | I <sub>O</sub> = -8.0 mA; V <sub>CC</sub> = 4.5 V                                      | 3.94 | -    | -    | V    |
| V <sub>OL</sub>                | LOW-level output voltage                         | V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub>                                    |      |      |      |      |
|                                |  | I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 2.0 V  | -    | 0    | 0.1  | V    |
|                                |  | I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 3.0 V  | -    | 0    | 0.1  | V    |
|                                |  | I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 4.5 V  | -    | 0    | 0.1  | V    |
|                                |  | I <sub>O</sub> = 4.0 mA; V <sub>CC</sub> = 3.0 V                                       | -    | -    | 0.36 | V    |
|                                | I <sub>O</sub> = 8.0 mA; V <sub>CC</sub> = 4.5 V | -  | -    | 0.36 | V    |      |
| I <sub>OZ</sub>                | 3-state OFF-state current                        | V <sub>I</sub> = V <sub>CC</sub> or GND; V <sub>CC</sub> = 5.5 V                       | -    | -    | 0.25 | µA   |
| I <sub>LI</sub>                | input leakage current                            | V <sub>I</sub> = V <sub>CC</sub> or GND; V <sub>CC</sub> = 5.5 V                       | -    | -    | 0.1  | µA   |
| I <sub>CC</sub>                | quiescent supply current                         | V <sub>I</sub> = V <sub>CC</sub> or GND; I <sub>O</sub> = 0 A; V <sub>CC</sub> = 5.5 V | -    | -    | 1.0  | µA   |
| C <sub>I</sub>                 | input capacitance                                |  | -    | 1.5  | 10   | pF   |

**Table 8: Static characteristics type 74AHC2G126 ...continued**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

| Symbol                                     | Parameter                 | Conditions   | Min  | Typ | Max  | Unit |
|--|---------------------------|--|------|-----|------|------|
| <b>T<sub>amb</sub> = -40 °C to +85 °C</b>  |                           |  |      |     |      |      |
| V <sub>IH</sub>                            | HIGH-level input voltage  | V <sub>CC</sub> = 2.0 V  | 1.5  | -   | -    | V    |
|  |                           | V <sub>CC</sub> = 3.0 V  | 2.1  | -   | -    | V    |
|  |                           | V <sub>CC</sub> = 5.5 V  | 3.85 | -   | -    | V    |
| V <sub>IL</sub>                            | LOW-level input voltage   | V <sub>CC</sub> = 2.0 V  | -    | -   | 0.5  | V    |
|  |                           | V <sub>CC</sub> = 3.0 V  | -    | -   | 0.9  | V    |
|  |                           | V <sub>CC</sub> = 5.5 V  | -    | -   | 1.65 | V    |
| V <sub>OH</sub>                            | HIGH-level output voltage | V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub>                                    |      |     |      |      |
|  |                           | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 2.0 V                                       | 1.9  | -   | -    | V    |
|  |                           | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 3.0 V                                       | 2.9  | -   | -    | V    |
|  |                           | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 4.5 V                                       | 4.4  | -   | -    | V    |
|  |                           | I <sub>O</sub> = -4.0 mA; V <sub>CC</sub> = 3.0 V                                      | 2.48 | -   | -    | V    |
|  |                           | I <sub>O</sub> = -8.0 mA; V <sub>CC</sub> = 4.5 V                                      | 3.8  | -   | -    | V    |
| V <sub>OL</sub>                            | LOW-level output voltage  | V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub>                                    |      |     |      |      |
|  |                           | I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 2.0 V  | -    | -   | 0.1  | V    |
|  |                           | I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 3.0 V  | -    | -   | 0.1  | V    |
|  |                           | I <sub>O</sub> = 50 µA; V <sub>CC</sub> = 4.5 V  | -    | -   | 0.1  | V    |
|  |                           | I <sub>O</sub> = 4.0 mA; V <sub>CC</sub> = 3.0 V                                       | -    | -   | 0.44 | V    |
|  |                           | I <sub>O</sub> = 8.0 mA; V <sub>CC</sub> = 4.5 V                                       | -    | -   | 0.44 | V    |
| I <sub>OZ</sub>                            | 3-state OFF-state current | V <sub>I</sub> = V <sub>CC</sub> or GND; V <sub>CC</sub> = 5.5 V                       | -    | -   | 2.5  | µA   |
| I <sub>LI</sub>                            | input leakage current     | V <sub>I</sub> = V <sub>CC</sub> or GND; V <sub>CC</sub> = 5.5 V                       | -    | -   | 1.0  | µA   |
| I <sub>CC</sub>                            | quiescent supply current  | V <sub>I</sub> = V <sub>CC</sub> or GND; I <sub>O</sub> = 0 A; V <sub>CC</sub> = 5.5 V | -    | -   | 10   | µA   |
| C <sub>I</sub>                             | input capacitance         |  | -    | -   | 10   | pF   |
| <b>T<sub>amb</sub> = -40 °C to +125 °C</b> |                           |  |      |     |      |      |
| V <sub>IH</sub>                            | HIGH-level input voltage  | V <sub>CC</sub> = 2.0 V  | 1.5  | -   | -    | V    |
|  |                           | V <sub>CC</sub> = 3.0 V  | 2.1  | -   | -    | V    |
|  |                           | V <sub>CC</sub> = 5.5 V  | 3.85 | -   | -    | V    |
| V <sub>IL</sub>                            | LOW-level input voltage   | V <sub>CC</sub> = 2.0 V  | -    | -   | 0.5  | V    |
|  |                           | V <sub>CC</sub> = 3.0 V  | -    | -   | 0.9  | V    |
|  |                           | V <sub>CC</sub> = 5.5 V  | -    | -   | 1.65 | V    |
| V <sub>OH</sub>                            | HIGH-level output voltage | V <sub>I</sub> = V <sub>IH</sub> or V <sub>IL</sub>                                    |      |     |      |      |
|  |                           | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 2.0 V                                       | 1.9  | -   | -    | V    |
|  |                           | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 3.0 V                                       | 2.9  | -   | -    | V    |
|  |                           | I <sub>O</sub> = -50 µA; V <sub>CC</sub> = 4.5 V                                       | 4.4  | -   | -    | V    |
|  |                           | I <sub>O</sub> = -4.0 mA; V <sub>CC</sub> = 3.0 V                                      | 2.40 | -   | -    | V    |
|  |                           | I <sub>O</sub> = -8.0 mA; V <sub>CC</sub> = 4.5 V                                      | 3.70 | -   | -    | V    |

**Table 8: Static characteristics type 74AHC2G126 ...continued**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

| Symbol   | Parameter                 | Conditions   | Min | Typ | Max | Unit    |
|----------|---------------------------|--|-----|-----|-----|---------|
| $V_{OL}$ | LOW-level output voltage  | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = 50 \mu A; V_{CC} = 2.0 \text{ V}$<br>$I_O = 50 \mu A; V_{CC} = 3.0 \text{ V}$<br>$I_O = 50 \mu A; V_{CC} = 4.5 \text{ V}$<br>$I_O = 4.0 \text{ mA}; V_{CC} = 3.0 \text{ V}$<br>$I_O = 8.0 \text{ mA}; V_{CC} = 4.5 \text{ V}$ | -   | -   | 0.1 | V       |
| $I_{OZ}$ | 3-state OFF-state current | $V_I = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$  | -   | -   | 10  | $\mu A$ |
| $I_{LI}$ | input leakage current     | $V_I = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$  | -   | -   | 2.0 | $\mu A$ |
| $I_{CC}$ | quiescent supply current  | $V_I = V_{CC}$ or GND; $I_O = 0 \text{ A}$ ;<br>$V_{CC} = 5.5 \text{ V}$   | -   | -   | 40  | $\mu A$ |
| $C_I$    | input capacitance         |  | -   | -   | 10  | pF      |

**Table 9: Static characteristics type 74AHCT2G126**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

| Symbol  | Parameter   | Conditions   | Min         | Typ      | Max         | Unit    |
|---|---|--|-------------|----------|-------------|---------|
| <b><math>T_{amb} = 25^\circ C</math></b>                              |   |  |             |          |             |         |
| $V_{IH}$  | HIGH-level input voltage                          | $V_{CC} = 4.5 \text{ V}$ to $5.5 \text{ V}$  | 2.0         | -        | -           | V       |
| $V_{IL}$  | LOW-level input voltage                           | $V_{CC} = 4.5 \text{ V}$ to $5.5 \text{ V}$  | -           | -        | 0.8         | V       |
| $V_{OH}$  | HIGH-level output voltage                         | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = -50 \mu A; V_{CC} = 4.5 \text{ V}$<br>$I_O = -8.0 \text{ mA}; V_{CC} = 4.5 \text{ V}$ | 4.4<br>3.94 | 4.5<br>- | -           | V       |
| $V_{OL}$  | LOW-level output voltage                          | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = 50 \mu A; V_{CC} = 4.5 \text{ V}$<br>$I_O = 8.0 \text{ mA}; V_{CC} = 4.5 \text{ V}$   | -<br>-      | 0<br>-   | 0.1<br>0.36 | V       |
| $I_{OZ}$  | 3-state OFF-state current                         | $V_I = V_{CC}$ or GND; $V_{CC} = 5.5 \text{ V}$  | -           | -        | 0.25        | $\mu A$ |
| $I_{LI}$  | input leakage current                             | $V_I = V_{IH}$ or $V_{IL}$ ; $V_{CC} = 5.5 \text{ V}$  | -           | -        | 0.1         | $\mu A$ |
| $I_{CC}$  | quiescent supply current                          | $V_I = V_{CC}$ or GND; $I_O = 0 \text{ A}$ ;<br>$V_{CC} = 5.5 \text{ V}$   | -           | -        | 1.0         | $\mu A$ |
| $\Delta I_{CC}$   | additional quiescent supply current per input pin | $V_I = 3.4 \text{ V}$ ; other inputs at $V_{CC}$ or GND; $I_O = 0 \text{ A}; V_{CC} = 5.5 \text{ V}$                       | -           | -        | 1.35        | mA      |
| $C_I$   | input capacitance                                 |  | -           | 1.5      | 10          | pF      |
| <b><math>T_{amb} = -40^\circ C</math> to <math>+85^\circ C</math></b> |   |  |             |          |             |         |
| $V_{IH}$  | HIGH-level input voltage                          | $V_{CC} = 4.5 \text{ V}$ to $5.5 \text{ V}$  | 2.0         | -        | -           | V       |
| $V_{IL}$  | LOW-level input voltage                           | $V_{CC} = 4.5 \text{ V}$ to $5.5 \text{ V}$  | -           | -        | 0.8         | V       |

**Table 9: Static characteristics type 74AHCT2G126 ...continued**

At recommended operating conditions; voltages are referenced to GND (ground = 0 V).

| Symbol   | Parameter   | Conditions   | Min | Typ | Max | Unit    |
|--|---|--|-----|-----|-----|---------|
| $V_{OH}$   | HIGH-level output voltage                         | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = -50 \mu A; V_{CC} = 4.5 V$<br>$I_O = -8.0 mA; V_{CC} = 4.5 V$ | 4.4 | —   | —   | V       |
| $V_{OL}$   | LOW-level output voltage                          | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = 50 \mu A; V_{CC} = 4.5 V$<br>$I_O = 8.0 mA; V_{CC} = 4.5 V$   | —   | —   | 0.1 | V       |
| $I_{OZ}$   | 3-state OFF-state current                         | $V_I = V_{CC}$ or GND; $V_{CC} = 5.5 V$  | —   | —   | 2.5 | $\mu A$ |
| $I_{LI}$   | input leakage current                             | $V_I = V_{IH}$ or $V_{IL}; V_{CC} = 5.5 V$   | —   | —   | 1.0 | $\mu A$ |
| $I_{CC}$   | quiescent supply current                          | $V_I = V_{CC}$ or GND; $I_O = 0 A;$<br>$V_{CC} = 5.5 V$  | —   | —   | 10  | $\mu A$ |
| $\Delta I_{CC}$  | additional quiescent supply current per input pin | $V_I = 3.4 V$ ; other inputs at $V_{CC}$ or GND; $I_O = 0 A; V_{CC} = 5.5 V$                       | —   | —   | 1.5 | mA      |
| $C_I$  | input capacitance                                 |  | —   | —   | 10  | pF      |
| <b><math>T_{amb} = -40^{\circ}\text{C}</math> to <math>+125^{\circ}\text{C}</math></b> |   |  |     |     |     |         |
| $V_{IH}$   | HIGH-level input voltage                          | $V_{CC} = 4.5 V$ to $5.5 V$  | 2.0 | —   | —   | V       |
| $V_{IL}$   | LOW-level input voltage                           | $V_{CC} = 4.5 V$ to $5.5 V$  | —   | —   | 0.8 | V       |
| $V_{OH}$   | HIGH-level output voltage                         | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = -50 \mu A; V_{CC} = 4.5 V$<br>$I_O = -8.0 mA; V_{CC} = 4.5 V$ | 4.4 | —   | —   | V       |
| $V_{OL}$   | LOW-level output voltage                          | $V_I = V_{IH}$ or $V_{IL}$<br>$I_O = 50 \mu A; V_{CC} = 4.5 V$<br>$I_O = 8.0 mA; V_{CC} = 4.5 V$   | —   | —   | 0.1 | V       |
| $I_{OZ}$   | 3-state OFF-state current                         | $V_I = V_{CC}$ or GND; $V_{CC} = 5.5 V$  | —   | —   | 10  | $\mu A$ |
| $I_{LI}$   | input leakage current                             | $V_I = V_{IH}$ or $V_{IL}; V_{CC} = 5.5 V$   | —   | —   | 2.0 | $\mu A$ |
| $I_{CC}$   | quiescent supply current                          | $V_I = V_{CC}$ or GND; $I_O = 0 A;$<br>$V_{CC} = 5.5 V$  | —   | —   | 40  | $\mu A$ |
| $\Delta I_{CC}$  | additional quiescent supply current per input pin | $V_I = 3.4 V$ ; other inputs at $V_{CC}$ or GND; $I_O = 0 A; V_{CC} = 5.5 V$                       | —   | —   | 1.5 | mA      |
| $C_I$  | input capacitance                                 |  | —   | —   | 10  | pF      |

## 12. Dynamic characteristics

**Table 10: Dynamic characteristics type 74AHC2G126***GND = 0 V;  $t_r = t_f \leq 3.0 \text{ ns}$ ; see [Figure 7](#).*

| Symbol                                    | Parameter                        | Test conditions   | Min  | Typ                                  | Max                                     | Unit                             |
|---|----------------------------------|---|--|--------------------------------------|---|----------------------------------|
| <b>T<sub>amb</sub> = 25 °C</b>            |                                  |   |  |                                      |   |                                  |
| t <sub>PHL</sub> , t <sub>PLH</sub>       | propagation delay<br>nA to nY    | see <a href="#">Figure 5</a><br><br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 50 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 50 pF                          | [1] -<br><br>[2] -<br><br>[1] -<br><br>[2] - | 4.7<br><br>3.4<br><br>6.6<br><br>4.8 | 8.0<br><br>5.5<br><br>11.5<br><br>7.5   | ns<br><br>ns<br><br>ns<br><br>ns |
| t <sub>PZH</sub> , t <sub>PZL</sub>       | propagation delay<br>nOE to nY   | see <a href="#">Figure 6</a><br><br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 50 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 50 pF                          | [1] -<br><br>[2] -<br><br>[1] -<br><br>[2] - | 5.0<br><br>3.6<br><br>6.9<br><br>4.9 | 8.0<br><br>5.1<br><br>11.5<br><br>7.5   | ns<br><br>ns<br><br>ns<br><br>ns |
| t <sub>PHZ</sub> , t <sub>PLZ</sub>       | propagation delay<br>nOE to nY   | see <a href="#">Figure 6</a> ; C <sub>L</sub> = 15 pF<br><br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 50 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 50 pF | [1] -<br><br>[2] -<br><br>[1] -<br><br>[2] - | 6.0<br><br>4.1<br><br>8.3<br><br>5.7 | 9.7<br><br>6.8<br><br>13.2<br><br>8.8   | ns<br><br>ns<br><br>ns<br><br>ns |
| C <sub>PD</sub>                           | power dissipation<br>capacitance | C <sub>L</sub> = 50 pF; f <sub>i</sub> = 1 MHz  | [3][4] -                                     | 10                                   | -                                       | pF                               |
| <b>T<sub>amb</sub> = -40 °C to +85 °C</b> |                                  |   |  |                                      |   |                                  |
| t <sub>PHL</sub> , t <sub>PLH</sub>       | propagation delay<br>nA to nY    | see <a href="#">Figure 5</a><br><br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 50 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 50 pF                          | 1.0<br><br>1.0<br><br>1.0<br><br>1.0         | -<br><br>-<br><br>-<br><br>-         | 9.5<br><br>6.5<br><br>13.0<br><br>8.5   | ns<br><br>ns<br><br>ns<br><br>ns |
| t <sub>PZH</sub> , t <sub>PZL</sub>       | propagation delay<br>nOE to nY   | see <a href="#">Figure 6</a><br><br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 50 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 50 pF                          | 1.0<br><br>1.0<br><br>1.0<br><br>1.0         | -<br><br>-<br><br>-<br><br>-         | 9.5<br><br>6.0<br><br>13.0<br><br>9.0   | ns<br><br>ns<br><br>ns<br><br>ns |
| t <sub>PHZ</sub> , t <sub>PLZ</sub>       | propagation delay<br>nOE to nY   | see <a href="#">Figure 6</a> ; C <sub>L</sub> = 15 pF<br><br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 15 pF<br>V <sub>CC</sub> = 3.0 V to 3.6 V; C <sub>L</sub> = 50 pF<br>V <sub>CC</sub> = 4.5 V to 5.5 V; C <sub>L</sub> = 50 pF | 1.0<br><br>1.0<br><br>1.0<br><br>1.0         | -<br><br>-<br><br>-<br><br>-         | 11.5<br><br>8.0<br><br>15.0<br><br>10.0 | ns<br><br>ns<br><br>ns<br><br>ns |

**Table 10: Dynamic characteristics type 74AHC2G126 ...continued**  
 $GND = 0 \text{ V}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ ; see [Figure 7](#).

| Symbol   | Parameter                      | Test conditions  | Min | Typ | Max  | Unit |
|--|--------------------------------|--|-----|-----|------|------|
| <b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +125 \text{ }^{\circ}\text{C}</math></b> |                                |  |     |     |      |      |
| $t_{PHL}, t_{PLH}$   | propagation delay<br>nA to nY  | see <a href="#">Figure 5</a><br><br>$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}; C_L = 15 \text{ pF}$<br>$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}; C_L = 15 \text{ pF}$<br>$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}; C_L = 50 \text{ pF}$<br>$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}; C_L = 50 \text{ pF}$                         | 1.0 | -   | 11.5 | ns   |
| $t_{PZH}, t_{PZL}$   | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a><br><br>$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}; C_L = 15 \text{ pF}$<br>$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}; C_L = 15 \text{ pF}$<br>$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}; C_L = 50 \text{ pF}$<br>$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}; C_L = 50 \text{ pF}$                         | 1.0 | -   | 11.5 | ns   |
| $t_{PHZ}, t_{PLZ}$   | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a> ; $C_L = 15 \text{ pF}$<br><br>$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}; C_L = 15 \text{ pF}$<br>$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}; C_L = 15 \text{ pF}$<br>$V_{CC} = 3.0 \text{ V to } 3.6 \text{ V}; C_L = 50 \text{ pF}$<br>$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}; C_L = 50 \text{ pF}$ | 1.0 | -   | 12.5 | ns   |
|  |                                |  | 1.0 | -   | 8.5  | ns   |
|  |                                |  | 1.0 | -   | 16.5 | ns   |
|  |                                |  | 1.0 | -   | 11.0 | ns   |

[1] Typical values are measured at  $V_{CC} = 3.3 \text{ V}$ .

[2] Typical values are measured at  $V_{CC} = 5.0 \text{ V}$ .

[3]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ).

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \Sigma(C_L \times V_{CC}^2 \times f_o) \text{ where:}$$

$f_i$  = input frequency in MHz;

$f_o$  = output frequency in MHz;

$C_L$  = output load capacitance in pF;

$V_{CC}$  = supply voltage in Volts;

N = total load switching outputs;

$\Sigma(C_L \times V_{CC}^2 \times f_o)$  = sum of the outputs.

[4] The condition is  $V_I = GND$  to  $V_{CC}$ .

**Table 11: Dynamic characteristics type 74AHCT2G126**

$GND = 0 \text{ V}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ ;  $V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see [Figure 7](#)

| Symbol  | Parameter                      | Test conditions  | Min | Typ | Max | Unit |
|---|--------------------------------|--|-----|-----|-----|------|
| <b><math>T_{amb} = 25 \text{ }^{\circ}\text{C}</math> [1]</b> |                                |  |     |     |     |      |
| $t_{PHL}, t_{PLH}$  | propagation delay<br>nA to nY  | see <a href="#">Figure 5</a><br><br>$C_L = 15 \text{ pF}$<br>$C_L = 50 \text{ pF}$ | -   | 3.4 | 5.5 | ns   |
| $t_{PZH}, t_{PZL}$  | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a><br><br>$C_L = 15 \text{ pF}$<br>$C_L = 50 \text{ pF}$ | -   | 3.9 | 5.1 | ns   |
| $t_{PHZ}, t_{PLZ}$  | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a><br><br>$C_L = 15 \text{ pF}$<br>$C_L = 50 \text{ pF}$ | -   | 4.5 | 6.8 | ns   |
|   |                                |  | -   | 6.1 | 8.8 | ns   |

**Table 11: Dynamic characteristics type 74AHCT2G126 ...continued**  
 $GND = 0 \text{ V}$ ;  $t_r = t_f \leq 3.0 \text{ ns}$ ;  $V_{CC} = 4.5 \text{ V to } 5.5 \text{ V}$ ; see [Figure 7](#)

| Symbol   | Parameter                      | Test conditions                               | Min    | Typ | Max  | Unit |    |
|--|--------------------------------|---|--------|-----|------|------|----|
| $C_{PD}$   | power dissipation capacitance  | $C_L = 50 \text{ pF}$ ; $f_i = 1 \text{ MHz}$ | [2][3] | -   | 10   | -    | pF |
| <b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +85 \text{ }^{\circ}\text{C}</math></b>  |                                |   |        |     |      |      |    |
| $t_{PHL}, t_{PLH}$   | propagation delay<br>nA to nY  | see <a href="#">Figure 5</a>                  |        |     |      |      |    |
|  |                                | $C_L = 15 \text{ pF}$                         | 1.0    | -   | 6.5  | ns   |    |
|  |                                | $C_L = 50 \text{ pF}$                         | 1.0    | -   | 8.5  | ns   |    |
| $t_{PZH}, t_{PZL}$   | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a>                  |        |     |      |      |    |
|  |                                | $C_L = 15 \text{ pF}$                         | 1.0    | -   | 6.0  | ns   |    |
|  |                                | $C_L = 50 \text{ pF}$                         | 1.0    | -   | 9.0  | ns   |    |
| $t_{PHZ}, t_{PLZ}$   | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a>                  |        |     |      |      |    |
|  |                                | $C_L = 15 \text{ pF}$                         | 1.0    | -   | 8.0  | ns   |    |
|  |                                | $C_L = 50 \text{ pF}$                         | 1.0    | -   | 10.0 | ns   |    |
| <b><math>T_{amb} = -40 \text{ }^{\circ}\text{C to } +125 \text{ }^{\circ}\text{C}</math></b> |                                |   |        |     |      |      |    |
| $t_{PHL}, t_{PLH}$   | propagation delay<br>nA to nY  | see <a href="#">Figure 5</a>                  |        |     |      |      |    |
|  |                                | $C_L = 15 \text{ pF}$                         | 1.0    | -   | 7.0  | ns   |    |
|  |                                | $C_L = 50 \text{ pF}$                         | 1.0    | -   | 9.5  | ns   |    |
| $t_{PZH}, t_{PZL}$   | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a>                  |        |     |      |      |    |
|  |                                | $C_L = 15 \text{ pF}$                         | 1.0    | -   | 6.5  | ns   |    |
|  |                                | $C_L = 50 \text{ pF}$                         | 1.0    | -   | 9.5  | ns   |    |
| $t_{PHZ}, t_{PLZ}$   | propagation delay<br>nOE to nY | see <a href="#">Figure 6</a>                  |        |     |      |      |    |
|  |                                | $C_L = 15 \text{ pF}$                         | 1.0    | -   | 8.5  | ns   |    |
|  |                                | $C_L = 50 \text{ pF}$                         | 1.0    | -   | 11.0 | ns   |    |

[1] Typical values are measured at  $V_{CC} = 5.0 \text{ V}$ .

[2]  $C_{PD}$  is used to determine the dynamic power dissipation ( $P_D$  in  $\mu\text{W}$ ).

$$P_D = C_{PD} \times V_{CC}^2 \times f_i \times N + \Sigma(C_L \times V_{CC}^2 \times f_o) \text{ where:}$$

$f_i$  = input frequency in MHz;

$f_o$  = output frequency in MHz;

$C_L$  = output load capacitance in pF;


$V_{CC}$  = supply voltage in Volts;

N = total load switching outputs;

$\Sigma(C_L \times V_{CC}^2 \times f_o)$  = sum of the outputs.


[3] The condition is  $V_I = GND$  to  $V_{CC}$ .


## 13. Waveforms



**Table 12: Measurement points**

| Type        | Input                  |                      | Output               |                         |                         |
|-------------|------------------------|----------------------|----------------------|-------------------------|-------------------------|
|             | V <sub>I</sub>         | V <sub>M</sub>       | V <sub>M</sub>       | V <sub>X</sub>          | V <sub>Y</sub>          |
| 74AHC2G126  | GND to V <sub>CC</sub> | 50 % V <sub>CC</sub> | 50 % V <sub>CC</sub> | V <sub>OL</sub> + 0.3 V | V <sub>OL</sub> - 0.3 V |
| 74AHCT2G126 | GND to 3.0 V           | 1.5 V                | 50 % V <sub>CC</sub> | V <sub>OL</sub> + 0.3 V | V <sub>OL</sub> - 0.3 V |





## 14. Package outline

TSSOP8: plastic thin shrink small outline package; 8 leads; body width 3 mm; lead length 0.5 mm SOT505-2





Fig 8. Package outline TSSOP8.

VSSOP8: plastic very thin shrink small outline package; 8 leads; body width 2.3 mm

SOT765-1

**DIMENSIONS (mm are the original dimensions)**

| UNIT | A<br>max. | A <sub>1</sub> | A <sub>2</sub> | A <sub>3</sub> | b <sub>p</sub> | c            | D <sup>(1)</sup> | E <sup>(2)</sup> | e   | H <sub>E</sub> | L   | L <sub>p</sub> | Q            | v   | w    | y   | Z <sup>(1)</sup> | θ        |
|------|-----------|----------------|----------------|----------------|----------------|--------------|------------------|------------------|-----|----------------|-----|----------------|--------------|-----|------|-----|------------------|----------|
| mm   | 1         | 0.15<br>0.00   | 0.85<br>0.60   | 0.12           | 0.27<br>0.17   | 0.23<br>0.08 | 2.1<br>1.9       | 2.4<br>2.2       | 0.5 | 3.2<br>3.0     | 0.4 | 0.40<br>0.15   | 0.21<br>0.19 | 0.2 | 0.13 | 0.1 | 0.4<br>0.1       | 8°<br>0° |

**Notes**

1. Plastic or metal protrusions of 0.15 mm maximum per side are not included.
2. Plastic or metal protrusions of 0.25 mm maximum per side are not included.

| OUTLINE<br>VERSION | REFERENCES |        |       |  | EUROPEAN<br>PROJECTION | ISSUE DATE |
|--------------------|------------|--------|-------|--|------------------------|------------|
|                    | IEC        | JEDEC  | JEITA |  |                        |            |
| SOT765-1           |            | MO-187 |       |  |                        | 02-06-07   |

**Fig 9. Package outline VSSOP8.**

## 15. Revision history

Table 13: Revision history

| Document ID       | Release date | Data sheet status | Change notice | Order number   | Supersedes |
|-------------------|--------------|-------------------|---------------|----------------|------------|
| 74AHC_AHCT2G126_1 | 20040304     | Product data      | -             | 9397 750 12698 | -          |

## 16. Data sheet status

| Level | Data sheet status [1] | Product status [2][3] | Definition   |
|-------|-----------------------|-----------------------|--|
| I     | Objective data        | Development           | This data sheet contains data from the objective specification for product development. Philips Semiconductors reserves the right to change the specification in any manner without notice.  |
| II    | Preliminary data      | Qualification         | This data sheet contains data from the preliminary specification. Supplementary data will be published at a later date. Philips Semiconductors reserves the right to change the specification without notice, in order to improve the design and supply the best possible product.             |
| III   | Product data          | Production            | This data sheet contains data from the product specification. Philips Semiconductors reserves the right to make changes at any time in order to improve the design, manufacturing and supply. Relevant changes will be communicated via a Customer Product/Process Change Notification (CPCN). |

[1] Please consult the most recently issued data sheet before initiating or completing a design.

[2] The product status of the device(s) described in this data sheet may have changed since this data sheet was published. The latest information is available on the Internet at URL <http://www.semiconductors.philips.com>.

[3] For data sheets describing multiple type numbers, the highest-level product status determines the data sheet status.

## 17. Definitions

**Short-form specification** — The data in a short-form specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.

**Limiting values definition** — Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 60134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

**Application information** — Applications that are described herein for any of these products are for illustrative purposes only. Philips Semiconductors make no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

## 18. Disclaimers

**Life support** — These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips Semiconductors customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips Semiconductors for any damages resulting from such application.

**Right to make changes** — Philips Semiconductors reserves the right to make changes in the products - including circuits, standard cells, and/or software - described or contained herein in order to improve design and/or performance. When the product is in full production (status 'Production'), relevant changes will be communicated via a Customer Product/Process Change Notification (CPCN). Philips Semiconductors assumes no responsibility or liability for the use of any of these products, conveys no license or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

## 19. Contact information

For additional information, please visit: <http://www.semiconductors.philips.com>

For sales office addresses, send an email to: [sales.addresses@www.semiconductors.philips.com](mailto:sales.addresses@www.semiconductors.philips.com)



## 20. Contents

|     |  |    |
|-----|--|----|
| 1   | General description .....              | 1  |
| 2   | Features .....                         | 1  |
| 3   | Quick reference data .....             | 1  |
| 4   | Ordering information .....             | 2  |
| 5   | Marking .....                          | 2  |
| 6   | Functional diagram .....               | 3  |
| 7   | Pinning information .....              | 3  |
| 7.1 | Pinning .....                          | 3  |
| 7.2 | Pin description .....                  | 3  |
| 8   | Functional description .....           | 4  |
| 8.1 | Function table .....                   | 4  |
| 9   | Limiting values .....                  | 4  |
| 10  | Recommended operating conditions ..... | 4  |
| 11  | Static characteristics .....           | 5  |
| 12  | Dynamic characteristics .....          | 9  |
| 13  | Waveforms .....                        | 12 |
| 14  | Package outline .....                  | 14 |
| 15  | Revision history .....                 | 16 |
| 16  | Data sheet status .....                | 17 |
| 17  | Definitions .....                      | 17 |
| 18  | Disclaimers .....                      | 17 |
| 19  | Contact information .....              | 17 |



© Koninklijke Philips Electronics N.V. 2004

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner. The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Date of release: 4 March 2004  
Document order number: 9397 750 12698

Published in The Netherlands